



Linea Classic S update interruptions

If the machine firmware update is interrupted, the machine will show the code "uSu" on the group 1 display.



If left untouched, the machine firmware installation will restart again from 0.

If the machine firmware update is interrupted, and the user presses the k1-1 (single shot on group 1) when the "uSu" code is shown, the bootloader freezes, preventing the firmware installation from being completed. As a result, the machine gets stuck.

This behaviour is present on the bootloader's 1.03 and 1.04 versions and can be resolved as follows:

- Bootloader **version 1.04**: while powering up, press k1-P and the tea button (continuous on group one plus tea button) to force the bootloader to resume the firmware installation.
- Bootloader **version 1.03**: a technician intervention is required as an old Linea Classic keyboard is required. The old keyboard needs to be plugged into group one, and the button combination to be pressed while powering up is k1-2 + k1-5 (single long shot + continuous on group 1).

When updating machines via the La Marzocco App, please ensure that the firmware installation is fully completed on the machine by following its status on the machine's display, and that the App confirms the update's success before operating the machine.

Once the update is completed the machine will be set to OFF.